

APPLICATION UNDER UNITED STATES PATENT LAWS

Atty. Dkt. No. PW 290647
(M#)

Invention: LITHOGRAPHIC APPARATUS, DEVICE MANUFACTURING METHOD,
AND DEVICE MANUFACTURED THEREBY

Inventor (s): Marcus Emile Joannes BOONMAN
Johannes Catharinus Hubertus MULKENS
Hans BUTLER



00909

Pillsbury Winthrop LLP

This is a:

- ☐ Provisional Application
- ☒ Regular Utility Application
- ☐ Continuing Application
 - ☒ The contents of the parent are incorporated by reference
- ☐ PCT National Phase Application
- ☐ Design Application
- ☐ Reissue Application
- ☐ Plant Application
- ☐ Substitute Specification
 - Sub. Spec Filed _____
 - in App. No. _____ / _____
- ☐ Marked up Specification re
 - Sub. Spec. filed _____
 - In App. No _____ / _____

SPECIFICATION

LITHOGRAPHIC APPARATUS, DEVICE MANUFACTURING METHOD, AND DEVICE MANUFACTURED THEREBY

BACKGROUND OF THE INVENTION

1. Field of the Invention

[0001] This application claims priority to EPC application number 01301116.8 filed February 8, 2001, herein incorporated by reference.

2. Background of the Related Art

[0002] The present invention relates generally to lithographic projection apparatus and more particularly to lithographic projection apparatus including a controller to adjust a shape of a focal plane of the projection system.

[0003] In general, a lithographic projection apparatus in accordance with embodiments of the present invention includes a radiation system for supplying a projection beam of radiation; a support structure for supporting patterning structure, the patterning structure serving to pattern the projection beam according to a desired pattern; a substrate table for holding a substrate; and a projection system for projecting the patterned beam onto a target portion of the substrate, said projection system having a focal plane and comprising at least one adjustable element capable of changing the shape of the focal plane.

[0004] The term "patterning structure" as here employed should be broadly interpreted as referring to structure that can be used to endow an incoming radiation beam with a patterned cross-section, corresponding to a pattern that is to be created in a target portion of the substrate; the term "light valve" can also be used in this context. Generally, the said pattern will correspond to a particular functional layer in a device being created in the target portion, such as an integrated circuit or other device (see below). Examples of such patterning structure include:

[0005] - A mask. The concept of a mask is well known in lithography, and it includes mask types such as binary, alternating phase-shift, and attenuated phase-shift, as well as various hybrid mask types. Placement of such a mask in the radiation beam causes selective transmission (in the case of a transmissive mask) or reflection (in the case of a reflective mask) of the radiation impinging on the mask, according to the pattern on the mask. In the case of a mask, the support structure will generally be a mask table, which ensures that the mask can be held at a desired position in the incoming radiation beam, and that it can be moved relative to the beam if so desired.

[0006] - A programmable mirror array. One example of such a device is a matrix-addressable surface having a viscoelastic control layer and a reflective surface. The basic principle behind such an apparatus is that (for example) addressed areas of the reflective surface reflect incident light as diffracted light, whereas unaddressed areas reflect incident light as undiffracted light. Using an appropriate filter, the said undiffracted light can be filtered out of the reflected beam, leaving only the diffracted light behind; in this manner, the beam becomes patterned according to the addressing pattern of the matrix-addressable surface. An alternative embodiment of a programmable mirror array employs a matrix arrangement of tiny mirrors, each of which can be individually tilted about an axis by applying a suitable localized electric field, or by employing piezoelectric actuation means. Once again, the mirrors are matrix-addressable, such that addressed mirrors will reflect an incoming radiation beam in a different direction to unaddressed mirrors; in this manner, the reflected beam is patterned according to the addressing pattern of the matrix-addressable mirrors. The required matrix addressing can be performed using suitable electronic means. In both of the situations described hereabove, the patterning structure can comprise one or more programmable mirror arrays. More information on mirror arrays as here referred to can be gleaned, for example, from United States Patents US 5,296,891 and US 5,523,193, and PCT patent applications WO 98/38597 and WO 98/33096, which are incorporated herein by reference. In the case of a programmable mirror array, the said support structure may be embodied as a frame or table, for example, which may be fixed or movable as required.

[0007] - A programmable LCD array. An example of such a construction is given in United States Patent US 5,229,872, which is incorporated herein by reference. As above, the support structure in this case may be embodied as a frame or table, for example, which may be fixed or movable as required.

[0008] For purposes of simplicity, the rest of this text may, at certain locations, specifically direct itself to examples involving a mask and mask table; however, the general principles discussed in such instances should be seen in the broader context of the patterning structure as hereabove set forth.

[0009] Lithographic projection apparatus can be used, for example, in the manufacture of integrated circuits (ICs). In such a case, the patterning structure may generate a circuit pattern corresponding to an individual layer of the IC, and this pattern can be imaged onto a target portion (e.g. comprising one or more dies) on a substrate (silicon wafer) that has been coated with a layer of radiation-sensitive material (resist). In general, a single wafer will contain a whole network of adjacent target portions that are successively irradiated via the projection system, one

at a time. In current apparatus, employing patterning by a mask on a mask table, a distinction can be made between two different types of machine. In one type of lithographic projection apparatus, each target portion is irradiated by exposing the entire mask pattern onto the target portion at once; such an apparatus is commonly referred to as a wafer stepper. In an alternative apparatus —commonly referred to as a step-and-scan apparatus — each target portion is irradiated by progressively scanning the mask pattern under the projection beam in a given reference direction (the "scanning" direction) while synchronously scanning the substrate table parallel or anti-parallel to this direction; since, in general, the projection system will have a magnification factor M (generally < 1), the speed V at which the substrate table is scanned will be a factor M times that at which the mask table is scanned. More information with regard to lithographic devices as here described can be gleaned, for example, from US 6,046,792, incorporated herein by reference.

[0010] In a manufacturing process using a lithographic projection apparatus, a pattern (e.g. in a mask) is imaged onto a substrate that is at least partially covered by a layer of radiation-sensitive material (resist). Prior to this imaging step, the substrate may undergo various procedures, such as priming, resist coating and a soft bake. After exposure, the substrate may be subjected to other procedures, such as a post-exposure bake (PEB), development, a hard bake and measurement/inspection of the imaged features. This array of procedures is used as a basis to pattern an individual layer of a device, e.g. an IC. Such a patterned layer may then undergo various processes such as etching, ion-implantation (doping), metallization, oxidation, chemo-mechanical polishing, etc., all intended to finish off an individual layer. If several layers are required, then the whole procedure, or a variant thereof, will have to be repeated for each new layer. Eventually, an array of devices will be present on the substrate (wafer). These devices are then separated from one another by a technique such as dicing or sawing, whence the individual devices can be mounted on a carrier, connected to pins, etc. Further information regarding such processes can be obtained, for example, from the book "Microchip Fabrication: A Practical Guide to Semiconductor Processing", Third Edition, by Peter van Zant, McGraw Hill Publishing Co., 1997, ISBN 0-07-067250-4, incorporated herein by reference.

[0011] For the sake of simplicity, the projection system may hereinafter be referred to as the "lens"; however, this term should be broadly interpreted as encompassing various types of projection system, including refractive optics, reflective optics, and catadioptric systems, for example. The radiation system may also include components operating according to any of these design types for directing, shaping or controlling the projection beam of radiation, and such components may also be referred to below, collectively or singularly, as a "lens". Further, the

lithographic apparatus may be of a type having two or more substrate tables (and/or two or more mask tables). In such "multiple stage" devices the additional tables may be used in parallel, or preparatory steps may be carried out on one or more tables while one or more other tables are being used for exposures. Dual stage lithographic apparatus are described, for example, in US 5,969,441 and WO 98/40791, incorporated herein by reference.

[0012] To correctly image the mask pattern onto the substrate it is necessary to position the wafer accurately in the focal plane of the projection lens. The position of the focal plane can vary according to the position of the mask, illumination and imaging settings in the illumination and projection systems and due to, for example, temperature and/or pressure variations in the apparatus, during an exposure or series of exposures. To deal with these variations in focal plane position, it is known to measure the vertical position of the focal plane using a sensor such as a transmission image sensor (TIS) or a reflection image sensor (RIS) and then position the wafer surface in the focal plane. This can be done using so-called "on-the-fly" leveling whereby a level sensor measures the vertical position of the wafer surface during the exposure and adjusts the height and/or tilt of the wafer table to optimize the imaging performance. Alternatively, so-called "off-axis" leveling can be used. In this method, a height map of (a part of) the wafer surface is taken, e.g. in a multi-stage apparatus, in advance of the exposure and height and tilt set points for the exposure, or series of exposures, to optimize the focus according to defined criteria, are calculated in advance. Methods and a system for such off-axis leveling are described in European Patent Application EP-A-1 037 117. In the off-axis method, it is proposed that the exact shape and position of the wafer surface be measured and the wafer height and tilt positions for the exposure can then be optimized to minimize defocus predicted relative to that measured wafer surface. Since the focal plane of the projection system will generally be flat and the wafer surface will generally not be flat, there will always be some residual defocus which cannot be compensated for by leveling procedures.

SUMMARY OF THE INVENTION

[0013] One aspect of embodiments of the present invention includes a system and a method for controlling a lithographic projection apparatus to further improve focus across the entire exposure area.

[0014] This and other aspects are achieved according to embodiments of the invention in a lithographic apparatus as specified in the opening paragraph, characterized by:

[0015] a controller, operative during an exposure for imaging the irradiated portion, to control said adjustable element to change the shape of said focal plane to more closely conform to the surface contour of said exposure area.

[0016] As discussed above, certain methods in which the focal plane is generally arranged to be as flat as possible and the substrate height and/or tilt are controlled to minimize defocus, inevitably leave some residual defocus as the wafer surface is generally not exactly flat. According to the present invention, rather than attempting to make the focal plane exactly flat, its shape is deliberately changed to make it conform more closely to the measured surface contour of the substrate in the exposure area to be exposed. Control of the wafer height and tilt is integrated with control of the shape of the focal plane. Then, low order (height and tilt) corrections can be effected by positioning the substrate and high order corrections can be effected by adjustments to the shape of the focal plane. Also, low order effects of high order adjustments to the shape of the focal plane can be compensated for in positioning of the substrate.

[0017] Embodiments of the present invention can therefore provide improved imaging by reducing defocus across the entire exposure area. This improves imaging quality on all exposure areas and also makes possible focusing on exposure areas having curved surfaces that would previously have exceeded defocus limits.

[0018] Embodiments of the present invention can make use of all available manipulators in the projection system to adjust elements that affect the shape of the focal plane. Such manipulators are provided with suitable actuators, e.g. motors, piezoelectric actuators, solenoids, etc., to enable the a controller to adjust the elements to which the manipulators are connected. The adjustable elements may include elements specifically provided for the present invention or provided for other purposes such as correcting field curvature introduced by changes in magnification, or correcting astigmatisms in the lenses. The adjustable elements may have their position and/or orientation in any of the six degrees of freedom changed by the manipulators. Additionally, it is possible to adjust the shape of the element, e.g. where the element is a reflector provided with piezoelectric elements for adjusting its surface figure.

[0019] According to a further aspect of embodiments of the invention there is provided a device manufacturing method comprising the steps of:

[0020] providing a substrate that is at least partially covered by a layer of radiation-sensitive material;

[0021] providing a projection beam of radiation using a radiation system;

[0022] using patterning structure to endow the projection beam with a pattern in its cross-section; and

[0023] projecting the patterned beam of radiation onto a target portion of the layer of radiation-sensitive material using a projection system, said projection system having a focal plane and comprising at least one adjustable element capable of changing the shape of the focal plane;

[0024] characterized by the step of:

[0025] controlling said adjustable element during the step of imaging to change the shape of said focal plane to more closely conform to the surface contour of said exposure area.

[0026] Although specific reference may be made in this text to the use of the apparatus according to the invention in the manufacture of ICs, it should be explicitly understood that such an apparatus has many other possible applications. For example, it may be employed in the manufacture of integrated optical systems, guidance and detection patterns for magnetic domain memories, liquid-crystal display panels, thin-film magnetic heads, etc. The skilled artisan will appreciate that, in the context of such alternative applications, any use of the terms "reticle", "wafer" or "die" in this text should be considered as being replaced by the more general terms "mask", "substrate" and "target portion", respectively.

[0027] In the present document, the terms "radiation" and "beam" are used to encompass all types of electromagnetic radiation, including ultraviolet radiation (e.g. with a wavelength of 365, 248, 193, 157 or 126 nm) and EUV (extreme ultra-violet radiation, e.g. having a wavelength in the range 5-20 nm), as well as particle beams, such as ion beams or electron beams.

BRIEF DESCRIPTION OF THE DRAWINGS

[0028] The invention and its attendant advantages will be further described below with reference to exemplary embodiments and the accompanying schematic drawings, in which:

[0029] Figure 1 depicts a lithographic projection apparatus according to a first embodiment of the invention;

[0030] Figure 2 is a view showing how the wafer height is determined from measurements by the level sensor and the Z-interferometer;

[0031] Figures 3 to 6 are views showing various steps of the focus control and leveling procedure according to the present invention;

[0032] Figure 7 is a plan view of a substrate table showing the sensors and fiducials used in the focus control and leveling procedure according to the present invention;

[0033] Figure 8 is a view showing adjustable elements in the projection lens used in the present invention; and

[0034] Figure 9 is a diagram of a control system for putting the present invention into effect.

[0035] In the drawings, like references indicate like parts.

DETAILED DESCRIPTION

[0036] Figure 1 schematically depicts a lithographic projection apparatus according to a particular embodiment of the invention. The apparatus comprises:

[0037] a radiation system LA, IL (EX, IN, CO), for supplying a projection beam PB of radiation (eg. UV or EUV radiation). In this particular case, the radiation system also comprises a radiation source LA;

[0038] a first object table (mask table) MT provided with a mask holder for holding a mask MA (eg. a reticle), and connected to first positioning means for accurately positioning the mask with respect to item PL;

[0039] a second object table (substrate table) WTa provided with a substrate holder for holding a substrate W (eg. a resist-coated silicon wafer), and connected to second positioning means for accurately positioning the substrate with respect to item PL;

[0040] a third object table (substrate or wafer table) WTb provided with a substrate holder for holding a substrate W (eg. a resist-coated silicon wafer), and connected to third positioning means for accurately positioning the substrate with respect to item PL;

[0041] a measurement system MS for performing measurement (characterization) processes on a substrate held on a substrate table WTa or WTb at a measurement station

[0042] a projection system ("lens") PL (eg. a refractive or catadioptric system, a mirror group or an array of field deflectors) for imaging an irradiated portion of the mask MA onto a target portion C (eg. comprising one or more dies) of the substrate W held on a substrate table WTa or WTb at an exposure station.

[0043] As here depicted, the apparatus is of a transmissive type (*i.e.* has a transmissive mask). However, in general, it may also be of a reflective type, for example (with a reflective mask). Alternatively, the apparatus may employ another kind of patterning structure, such as a programmable mirror array of a type as referred to above.

[0044] The source LA (eg. a Hg lamp, an excimer laser, a laser-produced plasma source, a discharge plasma source, an undulator provided around the path of an electron beam in a storage ring or synchrotron, or an electron or ion beam source) produces a beam of radiation. This beam

is fed into an illumination system (illuminator) IL, either directly or after having traversed conditioning means, such as a beam expander EX, for example. The illuminator IL may comprise adjusting means AM for setting the outer and/or inner radial extent (commonly referred to as σ -outer and σ -inner, respectively) of the intensity distribution in the beam. In addition, it will generally comprise various other components, such as an integrator IN and a condenser CO. In this way, the beam PB impinging on the mask MA has a desired uniformity and intensity distribution in its cross-section.

[0045] It should be noted with regard to Figure 1 that the source LA may be within the housing of the lithographic projection apparatus (as is often the case when the source LA is a mercury lamp, for example), but that it may also be remote from the lithographic projection apparatus, the radiation beam which it produces being led into the apparatus (e.g. with the aid of suitable directing mirrors); this latter scenario is often the case when the source LA is an excimer laser. The current invention and Claims encompass both of these scenarios.

[0046] The beam PB subsequently intercepts the mask MA, which is held on a mask table MT. Having traversed the mask MA, the beam PB passes through the lens PL, which focuses the beam PB onto a target portion C of the substrate W. With the aid of the interferometric measuring means IF, the substrate tables WTa, WTb can be moved accurately by the second and third positioning means, e.g. so as to position different target portions C in the path of the beam PB. Similarly, the first positioning means can be used to accurately position the mask MA with respect to the path of the beam PB, e.g. after mechanical retrieval of the mask MA from a mask library, or during a scan. In general, movement of the object tables MT, WTa, WTb will be realized with the aid of a long-stroke module (coarse positioning) and a short-stroke module (fine positioning), which are not explicitly depicted in Figure 1. However, in the case of a wafer stepper (as opposed to a step-and-scan apparatus) the mask table MT may just be connected to a short stroke actuator, or may be fixed.

[0047] The second and third positioning means may be constructed so as to be able to position their respective substrate tables WTa, WTb over a range encompassing both the exposure station under projection system PL and the measurement station under the measurement system MS. Alternatively, the second and third positioning means may be replaced by separate exposure station and measurement station positioning systems for positioning a substrate table in the respective exposure stations and a table exchange means for exchanging the substrate tables between the two positioning systems. Suitable positioning systems are described, inter alia, in WO 98/28665 and WO 98/40791 mentioned above. It should be noted that a lithography

apparatus may have multiple exposure stations and/or multiple measurement stations and that the numbers of measurement and exposure stations may be different than each other and the total number of stations need not equal the number of substrate tables. Indeed, the principle of separate exposure and measurement stations may be employed even with a single substrate table.

[0048] The depicted apparatus can be used in two different modes:

[0049] 1. In step mode, the mask table MT is kept essentially stationary, and an entire mask image is projected at once (*i.e.* a single "flash") onto a target portion C. The substrate table WTa or WTb is then shifted in the x and/or y directions so that a different target portion C can be irradiated by the beam PB;

[0050] 2. In scan mode, essentially the same scenario applies, except that a given target portion C is not exposed in a single "flash". Instead, the mask table MT is movable in a given direction (the so-called "scan direction", *e.g.* the y direction) with a speed u so that the projection beam PB is caused to scan over a mask image; concurrently, the substrate table WTa or WTb is simultaneously moved in the same or opposite direction at a speed $V = Mu$ in which M is the magnification of the lens PL (typically, $M = 1/4$ or $1/5$). In this manner, a relatively large target portion C can be exposed, without having to compromise on resolution.

[0051] An important factor influencing the imaging quality of a lithographic apparatus is the accuracy with which the mask image is focused on the substrate. Wafers are generally polished to a very high degree of flatness but nevertheless deviations of the wafer surface from perfect flatness (referred to as "unflatness") of sufficient magnitude noticeably to affect focus accuracy can occur. Unflatness may be caused, for example, by variations in wafer thickness, distortion of the shape of the wafer or contaminants on the substrate table. The presence of structures due to previous process steps also significantly affects the wafer height (flatness). In the present invention, the cause of unflatness is largely irrelevant; only the height of the top surface of the wafer is considered. Unless the context otherwise requires, references below to "the wafer surface" refer to the top surface of the wafer onto which will be projected the mask image.

[0052] After loading a wafer onto one of the substrate tables WTa, WTb, the height of the wafer surface Z_{Wafer} relative to a physical reference surface of the substrate table is mapped. This process is carried out at the measurement station using a first sensor, referred to as the level sensor, which measures the vertical (Z) position of the physical reference surface and the vertical position of the wafer surface, Z_{LS} , at a plurality of points, and a second sensor, for example a Z-interferometer, which simultaneously measures the vertical position of the substrate table, Z_{IF} at the same points. As shown in Figure 2, the wafer surface height is determined as $Z_{\text{Wafer}} = Z_{\text{LS}}$

- ZIF. The substrate table carrying the wafer is then transferred to the exposure station and the vertical position of the physical reference surface is again determined. The height map is then referred to in positioning the wafer at the correct vertical position during the exposure process. This procedure is described in more detail below with reference to Figures 3 to 6.

[0053] As shown in Figure 3, first the substrate table is moved so that a physical reference surface fixed to the substrate table is underneath the level sensor LS. The physical reference surface may be any convenient surface whose position in X, Y and Z on the substrate table will not change during processing of a wafer in the lithographic apparatus and, most importantly, in the transfer of the substrate table between measurement and exposure stations. The physical reference surface may be part of a fiducial containing other alignment markers and the surface should have such properties as to allow its vertical position to be measured by the same sensor as measures the vertical position of the wafer surface. The physical reference surface may be a reflective surface in a fiducial in which is inset a so-called transmission image sensor (TIS). The TIS is described further below.

[0054] The level sensor may be, for example, an optical sensor; alternatively, pneumatic or capacitive sensors (for example) are conceivable. A presently preferred form of sensor making use of Moiré patterns formed between the image of a projection grating reflected by the wafer surface and a fixed detection grating is described in European Patent Application EP-A-1 037 117. The level sensor should preferably measure the vertical position of a plurality of positions on the wafer surface simultaneously and for each position the sensor may measure the average height of a particular area, so averaging out unflatnesses of high spatial frequencies.

[0055] Simultaneously with the measurement of the vertical position of a physical reference surface by the level sensor LS, the vertical position of the substrate table is measured using the Z-interferometer, ZIF. The Z-interferometer may, for example, be part of a three, five or six-axis interferometric metrology system such as that described in WO 99/28790 or WO 99/32940, which documents are incorporated herein by reference. The Z-interferometer system preferably measures the vertical position of the substrate table at a point having the same position in the XY plane as the calibrated measurement position of the level sensor LS. This may be done by measuring the vertical position of two opposite sides of the substrate table WT (WTa or WTb) at points in line with the measurement position of the level sensor and interpolating/modeling between them. This ensures that, in the event that the substrate table is tilted out of the XY plane, the Z-interferometer measurement correctly indicates the vertical position of the substrate table under the level sensor.

[0056] Preferably, this process is repeated with at least a second physical reference surface spaced apart, e.g. diagonally, from the first physical reference surface. Height measurements from two or more positions can then be used to define a reference plane.

[0057] The simultaneous measurement of the vertical position of one or more physical reference surfaces and the vertical position of the substrate table establishes a point or points determining the reference plane relative to which the wafer height is to be mapped. A Z-interferometer of the type mentioned above is effectively a displacement sensor rather than an absolute sensor, and so requires zeroing, but provides a highly linear position measurement over a wide range. On the other hand, suitable level sensors, e.g. those mentioned above, may provide an absolute position measurement with respect to an externally defined reference plane (i.e. nominal zero) but over a smaller range. Where such sensors are used, it is convenient to move the substrate table vertically under the level sensor until the physical reference surface(s) is (are) positioned at a nominal zero in the middle of the measurement range of the level sensor and to read out the current interferometer Z value. One or more of these measurements on physical reference surfaces will establish the reference plane for the height mapping. The Z-interferometer is then zeroed with reference to the reference plane. In this way the reference plane is related to the physical surface on the substrate table and the Z-Wafer height map is made independent of the initial zero position of the Z-interferometer at the measurement station and other local factors such as any unflatness in the base plate over which the substrate table is moved. Additionally, the height map is made independent of any drift in the zero position of the level sensor.

[0058] As illustrated in Figure 4, once the reference plane has been established, the substrate table is moved so that the wafer surface is scanned underneath the level sensor to make the height map. The vertical position of the wafer surface and the vertical position of the substrate table are measured at a plurality of points of known XY position and subtracted from each other to give the wafer height at the known XY positions. These wafer height values form the wafer height map which can be recorded in any suitable form. For example, the wafer height values and XY coordinates may be stored together in so-called indivisible pairs. Alternatively, the points at which wafer height values are taken may be predetermined, e.g. by scanning the wafer along a predetermined path at a predetermined speed and making measurements at predetermined intervals, so that a simple list or array of height values (optionally together with a small number of parameters defining the measurement pattern and/or a starting point) may suffice to define the height map.

[0059] The motion of the substrate table during the height mapping scan is largely only in the XY plane. However, if the level sensor LS is of a type which only gives a reliable zero reading,

the substrate table is also moved vertically to keep the wafer surface at the zero position of the level sensor. The wafer height is then essentially derived from the Z movements of the substrate table, as measured by the Z-interferometer, necessary to maintain a zero readout from the level sensor. However, it is preferable to use a level sensor that has an appreciable measurement range over which its output is linearly related to wafer height, or can be linearized. Such measurement range ideally encompasses the maximum expected, or permissible, variation in wafer height. With such a sensor, the need for vertical movement of the substrate table during the scan is reduced or eliminated and the scan can be completed faster, since the scan speed is then limited by the sensor response time rather than by the ability of the short stroke positioning of the substrate table to track the contour of the wafer in three dimensions. Also, a sensor with an appreciable linear range can allow the heights at a plurality of positions (e.g. an array of spots) to be measured simultaneously.

[0060] Next, the wafer table is moved to the exposure station and, as shown in Figure 5, the (physical) reference surface is positioned under the projection lens so as to allow a measurement of its vertical position relative to a reference point in the focal plane of the projection lens. In a preferred embodiment, this is achieved using one or more transmission image sensors (described below) whose detector is physically connected to the reference surface used in the earlier measurements. The transmission image sensor(s) can determine the vertical focus position of the projected image from the mask under the projection lens. Armed with this measurement, the reference plane can be related to the focal plane of the projection lens and an exposure scheme which keeps the wafer surface in optimum focus can be determined. In the prior art this is done by calculating a path for the substrate table in three-dimensions, e.g. defined by Z, Rx and Ry setpoints for a series of points along the scan path. This is shown in Figure 6. According to the present invention, the shape of the focal plane is also adjusted to improve the focus using available manipulators in the projection lens. This is shown in Figure 8.

[0061] As can be seen in Figure 8, if the wafer surface WS includes significant unflatness, it is impossible to bring it into correct focus in a flat focal plane 11 across the entire area of the exposure slit of the projection beam PB. Instead, it is necessary to position the wafer at a position that minimizes the total or average defocus between the wafer surface WS and the flat focal plane 11. According to the invention, the residual defocus can be minimized or eliminated by distorting the focal plane using available manipulators 22, 24, 26 in the projection system PL. Such manipulators 22, 24, 26 may adjust the vertical, horizontal and/or rotational positions of elements 21, 23, 25 in the projection systems. The manipulators used in the present invention may be provided for on-site adjustment of the projection lens, for compensating for transient

effects, e.g. lens heating caused by the projection beam, or specifically for the present invention. Lens elements used to correct field curvature caused by adjustments in the magnification of the system are particularly useful in the present invention. According to the invention, the field curvature corrections can be changed, or field curvature deliberately introduced to improve focus on a non-flat substrate. Of course, any other available manipulators which change the (relative) position and/or orientation of one or more lens elements may be used. The invention may also make use of manipulators which change the shape and/or optical properties of elements in the projection system.

[0062] The degree of improvement afforded by the present invention will depend on the wafer surface and the number and effect of the available manipulators. As can be seen in Figure 8, introducing a second order correction results in a focal plane 12 which is closer to the illustrated wafer surface and hence has a reduced defocus. Introducing a fourth order correction results in a focal plane 13 even closer to the wafer surface WS and hence further reduced defocus. If the projection system includes asymmetric elements and suitable manipulators, higher odd order corrections can also be made.

[0063] According to the invention, setpoints for p1, p2, etc., where p1, p2, etc. are adjustable parameters of the projection system PL, are determined in addition to setpoints for Z, Rx and Ry. The setpoints can be determined using a least squares method so as to minimize the difference between the wafer map data and the focus plane of the exposure slit image, during the scanning motion. For ease of calculation, the relative motion of the exposure slit image and wafer can be expressed as the slit moving relative to a static wafer. The least squares criterion can then be expressed as, for each time t, finding the values Z(t), Rx(t), Ry(t), p1(t), p2(t), ... etc. which give a minimum value of:

$$LSQ(t) = \frac{1}{s.W} \int_{-s/2}^{+s/2} \int_{-W/2}^{+W/2} [w(x, y, Z(t), x.Ry(t), y.Rx(t)) - FP(p1(t), p2(t), etc.)]^2 dx dy \quad (1)$$

[0064] where $w(x, y, etc.)$ defines the vertical position of the wafer surface, $FP(p1(t), p2(t), etc.)$ defines the vertical position of the focal plane as a function of p1(t), p2(t), etc, s is the width of the exposure slit in the scanning direction and W its length perpendicular to the scanning direction. The setpoints and the wafer trajectory can be expressed as functions of either Y (position in the scanning direction) or t (time) since these are related by $Y = y_0 + v.t$, where y_0 is the starting position and v is the scanning speed.

[0065] As mentioned above, the physical reference surface(s) is (are) preferably a surface in which a transmission image sensor (TIS) is inset. As shown in Figure 7, two sensors TIS1 and

TIS2 are mounted on a fiducial plate mounted to the top surface of the substrate table (WT, WTa or WTb), at diagonally opposite positions outside the area covered by the wafer W. The fiducial plate is made of a highly stable material with a very low coefficient of thermal expansion, e.g. Invar, and has a flat reflective upper surface which may carry markers used in alignment processes. TIS1 and TIS2 are sensors used to determine directly the vertical (and horizontal) position of the aerial image of the projection lens. They comprise apertures in the respective surface close behind which is placed a photodetector sensitive to the radiation used for the exposure process. To determine the position of the focal plane, the projection lens projects into space an image of a TIS pattern TIS-M provided on the mask MA and having contrasting light and dark regions. The substrate table is then scanned horizontally (in one or preferably two directions) and vertically so that the aperture of the TIS passes through the space where the aerial image is expected to be. As the TIS aperture passes through the light and dark portions of the image of the TIS pattern, the output of the photodetector will fluctuate. This procedure is repeated at different vertical levels. The position at which the rate of change of amplitude of the photodetector output is highest indicates the position at which the image of TIS pattern has the greatest contrast and hence indicates the position of optimum focus. Thereby, a three-dimensional map of the focal plane can be derived. An example of a TIS of this type is described in greater detail in US 4,540,277, incorporated herein by reference. Instead of the TIS, a Reflection Image Sensor (RIS) such as that described in US 5,144,363, incorporated herein by reference, may also be used.

[0066] Using the surface of the TIS as the physical reference surface has the advantage that the TIS measurement directly relates the reference plane used for the height map to the focal plane of the projection lens, and so the height map can be employed directly to give height corrections for the substrate table during the exposure process. This is illustrated in Figure 6, which shows the substrate table WT as positioned under the control of the Z-interferometer at a height determined by the height map so that the wafer surface is at the correct position under the projection lens PL.

[0067] The TIS surface may additionally carry reference markers whose position is detected using a through-the-lens (TTL) alignment system to align the substrate table to the mask. Such an alignment system is described in EP-O 467 445 A, incorporated herein by reference, for example. Alignment of individual exposure areas can also be carried out, or may be obviated by an alignment procedure carried out at the measurement stage to align the exposure areas to the reference markers on the substrate table. Such a procedure is described in EP-O 906 590 A, incorporated herein by reference, for example.

[0068] With knowledge of the location and extent of the intended exposure areas, the height map generated by the present invention can be used to calculate in advance optimum Z, Rx, Ry, p1, p2, etc. position setpoints for the substrate table or projection system for each exposure. This avoids the time required for leveling in known apparatus that only measure wafer height when the wafer is positioned under the projection lens, and hence increases throughput. The optimum Z, Rx, Ry, p1, p2, etc. setpoints may be calculated by various known mathematical techniques, for example using an iterative process to minimize defocus (defined as the distance between the wafer surface and the ideal focal plane), $LSQ(t)$, integrated over the exposure area.

[0069] A further advantage is possible in the step-and-scan mode. In this mode, the projection lens projects an image of only part of the mask pattern onto a corresponding part of the exposure area. The mask and substrate are then scanned in synchronism through the object and image focal planes of the projection system PL so that the entire mask pattern is imaged onto the whole exposure area. Although in practice the projection lens is held stationary and the mask and substrate are moved, it is often convenient to consider this process in terms of an image slit moving over the wafer surface. With the height map determined in advance by the present invention, it is possible to calculate a sequence of Z, Rx, Ry, p1, p2, etc. setpoints matched to the XY scan path (usually, scanning takes place in only one direction, e.g. Y). The sequence of setpoints can be optimized according to additional criteria, e.g. to minimize vertical accelerations or tilt motions that might reduce throughput or induce undesirable vibrations. Given a sequence of spaced-apart setpoints, a scanning trajectory for the exposure can be calculated using a polynomial or spline fitting procedure.

[0070] While the present invention aims to position the wafer at the optimum position in Z, Rx and Ry and adjust the shape of the focal plane for a given exposure, the variations in wafer surface height over the exposure area may be such that the wafer cannot be positioned and the focal plane shaped to give adequate focus over the entire area. Such so-called focus spots can result in an exposure failure. However, with the present invention such failures can be predicted in advance and remedial action can be taken. For example, the wafer may be stripped and re-coated without the detrimental effect of further processing a badly exposed wafer. Alternatively, if the predicted failure affects only one or a few devices on the wafer while others will be acceptable, throughput may be enhanced by skipping exposures that can be predicted in advance to result in defective devices.

[0071] A control system 30 used in implementing the present invention is shown in Figure 9. In Figure 9, data describing the wafer surface is supplied by wafer height map 31, which may comprise a memory in which a previously derived wafer height map has been stored, or a level

sensor directly measuring the wafer surface, in real time, and data describing the focal plane from focal plane map 32. Since it is generally impractical to continuously measure the configuration of the focal plane, the focal plane map 32 is generally a memory storing the results of periodic measurements of the focal plane shape, supplemented as necessary by a model of how the focal plane changes with varying imaging parameters. Where continuous or quasi-continuous measurement of the focal plane is possible, that may also be used. The data describing the wafer surface and the focal plane shape is used by controller 33 to calculate setpoints for the substrate table position (Z, Rx and Ry) and projection lens parameters (p1, p2, etc.) which are supplied to servo controller 34 for table positioning and servo controller 35 for control of the manipulators 22, 24, 26 of the projection system PL. The table positioning servo controller 34 may employ a feedback control using the table position as measured by the interferometric displacement measuring system IF. The table position can also be used to control read-out from a memory 33a of setpoints calculated in advance. The adjustments to projection system parameters p1, p2, etc. can be fed back from the servo controller 35 to the focal plane map 32. The projection system may, as mentioned above, also be subject to adjustment to compensate for other, particularly transient, effects such as lens heating. Corrections to the projection system to effect the necessary compensations for such effects can be supplied by relevant control systems 36 and combined with adjustments for leveling and focusing according to the invention.

[0072] The control system 30 also includes a feedback from wafer height map 31 to servo controller 34 to allow control of the substrate table position in real time (on-the-fly). This feedback can be omitted if only off-axis leveling - in which the substrate table positions during the scan are stored in advance in memory - is to be performed.

[0073] How the necessary adjustments to arrive at optimum focus are divided among the different adjustable parameters will be determined as the invention is implemented in a specific apparatus. In many apparatus, the range of adjustment of the substrate table and its speed of response will be greater than those of the adjustable elements in the projection system. In such a case it can be convenient to separate the 0th and 1st order corrections from the higher order corrections and position the substrate table to correct for these; the 0th and 1st order correction are effectively height and tilt corrections whereas the higher order corrections represent variations in the wafer surface within the exposure slit which cannot therefore be compensated for by changing the height or tilt of the wafer surface. Although it is preferred to utilize the substrate table to perform the 0th or 1st order correction, it is also contemplated that these corrections are performed by adjusting adjustable elements in the projection system. Where separation of 0th and 1st order from higher order correction is utilized, the separation may be

done in the input data. For example, it would be possible to subtract the wafer surface and focal plane to derive a correction surface and for each exposure or point in the exposure path, then fit a flat, but inclined plane to the correction surface. The height of that flat plane at the center of the exposure slit determines the necessary height correction (0th order) and its inclination gives the necessary tilt corrections (1st order). The flat inclined plane is then subtracted from the correction surface leaving the higher orders for correction by adjustment of the projection lens parameters.

[0074] In some apparatus, adjustment of the projection lens parameters to achieve desired higher order corrections may cause unavoidable changes in the vertical position and inclination (0th and 1st order) of the focal plane. Where such crosstalk between the higher and lower order corrections occurs, an integrated control algorithm, rather than separation of the higher and lower orders, may be preferable. Alternatively, higher order corrections may be calculated first and any consequential effects in the lower order fed across into calculation of the necessary lower order corrections.

[0075] In scanning apparatus having an exposure slit that is relatively narrow in the scanning direction as compared to its width in the transverse direction (perpendicular to the scanning direction) and having mainly rotationally symmetric elements in the projection lens, the higher order corrections in particular may be performed mainly to compensate for the wafer surface shape in the transverse direction. This is because, with symmetric elements in the projection system, separate changes to the shape of the focal plane in the scanning and transverse directions are impossible. Thus, a change in the curvature of the focal plane in the transverse direction would result in a change in the scanning direction but because of the greater dimension of the exposure slit in the transverse direction, the curvatures that are necessary to compensate for deviations in the transverse direction would only result in small vertical deviations at the extremes in the scanning direction. Further, focus deviations in the scanning direction are averaged out by the scanning motion, and in many cases can therefore be disregarded.

[0076] Where the wafer shape is primarily determined by previous process layers and a number of similar or identical dies are to be printed on one or more wafers, it may be possible to predict or calculate corrections only once for each die type in a wafer or batch of wafers. In some cases, the higher order wafer shape may be determined by previous process layers but superimposed on height and tilt variations across and between wafers and/or exposure areas. In such a case, the higher order corrections for each die type may be calculated in advance and combined with lower order corrections calculated for each exposure area.

[0077] While we have described above specific embodiments of the invention it will be appreciated that the invention may be practiced otherwise than as described. The description is not intended to limit the invention.

100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000 1001 1002 1003 1004 1005 1006 1007 1008 1009 1010 1011 1012 1013 1014 1015 1016 1017 1018 1019 1020 1021 1022 1023 1024 1025 1026 1027 1028 1029 1030 1031 1032 1033 1034 1035 1036 1037 1038 1039 1040 1041 1042 1043 1044 1045 1046 1047 1048 1049 1050 1051 1052 1053 1054 1055 1056 1057 1058 1059 1060 1061 1062 1063 1064 1065 1066 1067 1068 1069 1070 1071 1072 1073 1074 1075 1076 1077 1078 1079 1080 1081 1082 1083 1084 1085 1086 1087 1088 1089 1090 1091 1092 1093 1094 1095 1096 1097 1098 1099 1100 1101 1102 1103 1104 1105 1106 1107 1108 1109 1110 1111 1112 1113 1114 1115 1116 1117 1118 1119 1120 1121 1122 1123 1124 1125 1126 1127 1128 1129 1130 1131 1132 1133 1134 1135 1136 1137 1138 1139 1140 1141 1142 1143 1144 1145 1146 1147 1148 1149 1150 1151 1152 1153 1154 1155 1156 1157 1158 1159 1160 1161 1162 1163 1164 1165 1166 1167 1168 1169 1170 1171 1172 1173 1174 1175 1176 1177 1178 1179 1180 1181 1182 1183 1184 1185 1186 1187 1188 1189 1190 1191 1192 1193 1194 1195 1196 1197 1198 1199 1200 1201 1202 1203 1204 1205 1206 1207 1208 1209 1210 1211 1212 1213 1214 1215 1216 1217 1218 1219 1220 1221 1222 1223 1224 1225 1226 1227 1228 1229 1230 1231 1232 1233 1234 1235 1236 1237 1238 1239 1240 1241 1242 1243 1244 1245 1246 1247 1248 1249 1250 1251 1252 1253 1254 1255 1256 1257 1258 1259 1260 1261 1262 1263 1264 1265 1266 1267 1268 1269 1270 1271 1272 1273 1274 1275 1276 1277 1278 1279 1280 1281 1282 1283 1284 1285 1286 1287 1288 1289 1290 1291 1292 1293 1294 1295 1296 1297 1298 1299 1300 1301 1302 1303 1304 1305 1306 1307 1308 1309 1310 1311 1312 1313 1314 1315 1316 1317 1318 1319 1320 1321 1322 1323 1324 1325 1326 1327 1328 1329 1330 1331 1332 1333 1334 1335 1336 1337 1338 1339 1340 1341 1342 1343 1344 1345 1346 1347 1348 1349 1350 1351 1352 1353 1354 1355 1356 1357 1358 1359 1360 1361 1362 1363 1364 1365 1366 1367 1368 1369 1370 1371 1372 1373 1374 1375 1376 1377 1378 1379 1380 1381 1382 1383 1384 1385 1386 1387 1388 1389 1390 1391 1392 1393 1394 1395 1396 1397 1398 1399 1400 1401 1402 1403 1404 1405 1406 1407 1408 1409 1410 1411 1412 1413 1414 1415 1416 1417 1418 1419 1420 1421 1422 1423 1424 1425 1426 1427 1428 1429 1430 1431 1432 1433 1434 1435 1436 1437 1438 1439 1440 1441 1442 1443 1444 1445 1446 1447 1448 1449 1450 1451 1452 1453 1454 1455 1456 1457 1458 1459 1460 1461 1462 1463 1464 1465 1466 1467 1468 1469 1470 1471 1472 1473 1474 1475 1476 1477 1478 1479 1480 1481 1482 1483 1484 1485 1486 1487 1488 1489 1490 1491 1492 1493 1494 1495 1496 1497 1498 1499 1500 1501 1502 1503 1504 1505 1506 1507 1508 1509 1510 1511 1512 1513 1514 1515 1516 1517 1518 1519 1520 1521 1522 1523 1524 1525 1526 1527 1528 1529 1530 1531 1532 1533 1534 1535 1536 1537 1538 1539 1540 1541 1542 1543 1544 1545 1546 1547 1548 1549 1550 1551 1552 1553 1554 1555 1556 1557 1558 1559 1560 1561 1562 1563 1564 1565 1566 1567 1568 1569 1570 1571 1572 1573 1574 1575 1576 1577 1578 1579 1580 1581 1582 1583 1584 1585 1586 1587 1588 1589 1590 1591 1592 1593 1594 1595 1596 1597 1598 1599 1600 1601 1602 1603 1604 1605 1606 1607 1608 1609 1610 1611 1612 1613 1614 1615 1616 1617 1618 1619 1620 1621 1622 1623 1624 1625 1626 1627 1628 1629 1630 1631 1632 1633 1634 1635 1636 1637 1638 1639 1640 1641 1642 1643 1644 1645 1646 1647 1648 1649 1650 1651 1652 1653 1654 1655 1656 1657 1658 1659 1660 1661 1662 1663 1664 1665 1666 1667 1668 1669 1670 1671 1672 1673 1674 1675 1676 1677 1678 1679 1680 1681 1682 1683 1684 1685 1686 1687 1688 1689 1690 1691 1692 1693 1694 1695 1696 1697 1698 1699 1700 1701 1702 1703 1704 1705 1706 1707 1708 1709 1710 1711 1712 1713 1714 1715 1716 1717 1718 1719 1720 1721 1722 1723 1724 1725 1726 1727 1728 1729 1730 1731 1732 1733 1734 1735 1736 1737 1738 1739 1740 1741 1742 1743 1744 1745 1746 1747 1748 1749 1750 1751 1752 1753 1754 1755 1756 1757 1758 1759 1760 1761 1762 1763 1764 1765 1766 1767 1768 1769 1770 1771 1772 1773 1774 1775 1776 1777 1778 1779 1780 1781 1782 1783 1784 1785 1786 1787 1788 1789 1790 1791 1792 1793 1794 1795 1796 1797 1798 1799 1800 1801 1802 1803 1804 1805 1806 1807 1808 1809 1810 1811 1812 1813 1814 1815 1816 1817 1818 1819 1820 1821 1822 1823 1824 1825 1826 1827 1828 1829 1830 1831 1832 1833 1834 1835 1836 1837 1838 1839 1840 1841 1842 1843 1844 1845 1846 1847 1848 1849 1850 1851 1852 1853 1854 1855 1856 1857 1858 1859 1860 1861 1862 1863 1864 1865 1866 1867 1868 1869 1870 1871 1872 1873 1874 1875 1876 1877 1878 1879 1880 1881 1882 1883 1884 1885 1886 1887 1888 1889 1890 1891 1892 1893 1894 1895 1896 1897 1898 1899 1900 1901 1902 1903 1904 1905 1906 1907 1908 1909 1910 1911 1912 1913 1914 1915 1916 1917 1918 1919 1920 1921 1922 1923 1924 1925 1926 1927 1928 1929 1930 1931 1932 1933 1934 1935 1936 1937 1938 1939 1940 1941 1942 1943 1944 1945 1946 1947 1948 1949 1950 1951 1952 1953 1954 1955 1956 1957 1958 1959 1960 1961 1962 1963 1964 1965 1966 1967 1968 1969 1970 1971 1972 1973 1974 1975 1976 1977 1978 1979 1980 1981 1982 1983 1984 1985 1986 1987 1988 1989 1990 1991 1992 1993 1994 1995 1996 1997 1998 1999 2000 2001 2002 2003 2004 2005 2006 2007 2008 2009 2010 2011 2012 2013 2014 2015 2016 2017 2018 2019 2020 2021 2022 2023 2024 2025 2026 2027 2028 2029 2030 2031 2032 2033 2034 2035 2036 2037 2038 2039 2040 2041 2042 2043 2044 2045 2046 2047 2048 2049 2050 2051 2052 2053 2054 2055 2056 2057 2058 2059 2060 2061 2062 2063 2064 2065 2066 2067 2068 2069 2070 2071 2072 2073 2074 2075 2076 2077 2078 2079 2080 2081 2082 2083 2084 2085 2086 2087 2088 2089 2090 2091 2092 2093 2094 2095 2096 2097 2098 2099 2100 2101 2102 2103 2104 2105 2106 2107 2108 2109 2110 2111 2112 2113 2114 2115 2116 2117 2118 2119 2120 2121 2122 2123 2124 2125 2126 2127 2128 2129 2130 2131 2132 2133 2134 2135 2136 2137 2138 2139 2140 2141 2142 2143 2144 2145 2146 2147 2148 2149 2150 2151 2152 2153 2154 2155 2156 2157 2158 2159 2160 2161 2162 2163 2164 2165 2166 2167 2168 2169 2170 2171 2172 2173 2174 2175 2176 2177 2178 2179 2180 2181 2182 2183 2184 2185 2186 2187 2188 2189 2190 2191 2192 2193 2194 2195 2196 2197 2198 2199 2200 2201 2202 2203 2204 2205 2206 2207 2208 2209 2210 2211 2212 2213 2214 2215 2216 2217 2218 2219 2220 2221 2222 2223 2224 2225 2226 2227 2228 2229 2230 2231 2232 2233 2234 2235 2236 2237 2238 2239 2240 2241 2242 2243 2244 2245 2246 2247 2248 2249 2250 2251 2252 2253 2254 2255 2256 2257 2258 2259 2260 2261 2262 2263 2264 2265 2266 2267 2268 2269 2270 2271 2272 2273 2274 2275 2276 2277 2278 2279 2280 2281 2282 2283 2284 2285 2286 2287 2288 2289 2290 2291 2292 2293 2294 2295 2296 2297 2298 2299 2300 2301 2302 2303 2304 2305 2306 2307 2308 2309 2310 2311 2312 2313 2314 2315 2316 2317 2318 2319 2320 2321 2322 2323 2324 2325 2326 2327 2328 2329 2330 2331 2332 2333 2334 2335 2336 2337 2338 2339 2340 2341 2342 2343 2344 2345 2346 2347 2348 2349 2350 2351 2352 2353 2354 2355 2356 2357 2358 2359 2360 2361 2362 2363 2364 2365 2366 2367 2368 2369 2370 2371 2372 2373 2374 2375 2376 2377 2378 2379 2380 2381 2382 2383 2384 2385 2386 2387 2388 2389 2390 2391 2392 2393 2394 2395 2396 2397 2398 2399 2400 2401 2402 2403 2404 2405 2406 2407 2408 2409 2410 2411 2412 2413 2414 2415 2416 2417 2418 2419 2420 2421 2422 2423 2424 2425 2426 2427 2428 2429 2430 2431 2432 2433 2434 2435 2436 2437 2438 2439 2440 2441 2442 2443 2444 2445 2446 2447 2448 2449 2450 2451 2452 2453 2454 2455 2456 2457 2458 2459 2460 2461 2462 2463 2464 2465 2466 2467 2468 2469 2470 2471 2472 2473 2474 2475 2476 2477 2478 2479 2480 2481 2482 2483 2484 2485 2486 2487 2488 2489 2490 2491 2492 2493 2494 2495 2496 2497 2498 2499 2500 2501 2502 2503 2504 2505 2506 2507 2508 2509 2510 2511 2512 2513 2514 2515 2516 2517 2518 2519 2520 2521 2522 2523 2524 2525 2526 2527 2528 2529 2530 2531 2532 2533 2534 2535 2536 2537 2538 2539 2540 2541 2542 2543 2544 2545 2546 2547 2548 2549 2550 2551 2552 2553 2554 2555 2556 2557 2558 2559 2560 2561 2562 2563 2564 2565 2566 2567 2568 2569 2570 2571 2572 2573 2574 2575 2576 2577 2578 2579 2580 2581 2582 2583 2584 2585 2586 2587 2588 2589 2590 2591 2592 2593 2594 2595 2596 2597 2598 2599 2600 2601 2602 2603 2604 2605 2606 2607 2608 2609 2610 2611 2612 2613 2614 2615 2616 2617 2618 2619 2620 2621 2622 2623 2624 2625 2626 2627 2628 2629 2630 2631 2632 2633 2634 2635 2636 2637 2638 2639 2640 2641 2642 2643 2644 2645 2646 2647 2648 2649 2650 2651 2652 2653 2654 2655 2656 2657 2658 2659 2660 2661 2662 2663 2664 2665 2666 2667 2668 2669 2670 2671 2672 2673 2674 2675 2676 2677 2678 2679 2680 2681 2682 2683 2684 2685 2686 2687 2688 2689 2690 2691 2692 2693 2694 2695 2696 2697 2698 2699 2700 2701 2702 2703 2704 2705 2706 2707 2708 2709 2710 2711 2712 2713 2714 2715 2716 2717 2718 2719 2720 2721 272